

CHOICE SELECT
CATV Video Module
CHO1006

This module is designed to amplify CATV signal plus two modulated sources and distributes all channels to eight different locations. It features bi-directional traffic with a 5-42MHz return path.

Specifications:

CATV Input: 47-806Mhz Gain: 3dB
Modulator input: 5-30Mhz insert loss: -14dB
Modulator input to TV output isolation >35dB
TV output to TV output isolation >30dB
Power: 15vdc/300ma

Module Installation:

- 1.) Place the module into the wiring enclosure.
- 2.) Position the module so that the tabs and hooks slip into the slots.
- 3.) Push black latch tabs into box to lock module.

Connection:

- 1.) Connect the incoming CATV line to the port labeled "CATV Input".
- 2.) Connect the first desired modulated source (such as DVD, VCR or satellite) to the port labeled "1st Modulated Source".
- 3.) Connect the second desired modulated source (such as security camera) to the port labeled "2nd Modulated Source".
- 4.) Connect the RG-6 Coaxial Cables from each destination to the "To TV outlets" ports labeled 1 thru 8.
- 5.) Connect AC/DC Power Adapter (included).

